

The Water Proof Ten Input Module 00-00935-000 is a member of Intellitec's Programmable Multiplex Control family. It works in combination with the PMC CPU or the IPX master and other standard, semi-custom, or custom I/O modules. The module can be used on either 12 or 24 volt systems.

The module provides ten digital inputs to the Intellitec multiplex systems. Each of these input channels is programmable to transmit to any of the 160 channels on a PMC loop. They can be programmed to be either high side or low side input to provide greater flexibility.

MODULE PROGRAMMABILITY

A number of parameters of the module are programmable, by the user, to provide a great deal of flexibility in its application. These parameters are set using a GUI on a PC and downloading it into the module through an on-board port. The programmable parameters include the following:

- channel allocation for each input
- input active state (high/pull up or low/pull down)
- input indicators on at active input or active input and test switch

LED DIAGNOSTIC INDICATORS

The Module includes a set of eleven diagnostic LED indicators to aid in the servicing of the associated system. Next to the input Deutsch DT style connector there are ten green LEDs. Each of these are associated with one of the inputs. These LED's indicate the active state of the input, regardless if it is high or low. To prevent excessive battery drain current, these LED's can be programmed to be on any time an input is active or only when it is active and the display button on the module is pressed.

There is also one red LED. This will illuminate if multiplex communications fail. In this case check the connections at J2.



The approximate module dimensions are 7.25" X 4.75" X 2.25" (184mm X 121mm X 57mm).

Works with Latching output modules

In the PMC system, the CPU is programmed to turn outputs on when the appropriate inputs are present. As with other input modules this module works the same way.

Because the module is programmable via a GUI, the inputs can be set to be on the same channel as a latching output. This provides additional flexibility when using the IPX master and latching output modules. If the input is set to the same channel as a latching output, that output will latch on and off as the input is toggled on and off.

SPECIFICATION

Module Part number 00-00935-000

Nominal Vehicle Voltage 12V or 24V

IPX Connections

J1-1	IPX +12 Volts
J1-2	IPX Communications
J1-3	IPX Ground

Mating Connectors

J1 Deutsch DT 03 2 S
J2 Deutsch DT 12 2 S

Output Connections

J2-1	Input 1
J2-2	Input 2
J2-3	Input 3
J2-4	Input 4
J2-5	Input 5
J2-6	Input 6
J2-7	Input 7
J2-8	Input 8
J2-9	Input 9
J2-10	Input 10
J2-11	Programming
J2-12	Programming

Module Set Up

There are a number of operating parameters that need to be set up in the module. They are set using a program on a PC with a GUI. This program is available from the Intellitec web site (www.Intellitec.com).

To program the module, a programming kit (10-01079-000) and an adapter harness (11-00935-000) is available from Intellitec.

